

ARCADE MAX

Cosmos



User
Manual



Contents

•	Contents	1
•	Package Contents	3
•	Get to Know Your Machine	5
○	Getting Inside	7
○	Wheels and Feet	9
○	Powering Up and Powering Down	10
○	Controlling the Lights	13
○	Volume Control	14
○	Gameplay Controls	15
○	Trackball	17
○	Light Guns	18
▪	Force-Feedback Recoil	19
•	Initial Set-Up	21
•	Connecting to the Internet	25
•	Light Gun Calibration	27
•	Using the Main Menu	31
○	Main Menu Controls (Main Panel)	32
○	Main Menu Controls (Light Gun)	33
○	Selecting a Game to Play	34
○	Adding a Favourite	35
•	Search Functionality	36
○	Using the Search Functionality	37
•	Background Download Mode	38

○	Background Download Mode Controls	39
○	How To Use	41
●	In-Game Controls	32
○	Main Panel	32
○	Light Gun	33
○	Pause Menu	46
○	Saving and Loading a Game	47
▪	About “States”	47
▪	How to Use	48
●	System Settings	50
○	Accessing the Settings Menu	51
○	Basic Menu Controls	52
○	Outline of Settings Menu Options	53
○	Game Setting Options	57
●	Machine Specifications	61
●	Troubleshooting	63

Package Contents

When you've unpackaged the machine, check below to ensure you have everything listed before getting started.



- A ArcadeMAX Cosmos Machine
- B Wireless Keyboard + Dongle
- C Power Cable
- D Access Keys (attached to joystick)
- E Instruction Booklet
- F SSD Card Reader + USB Cable

This page is intentionally left blank


Get to Know Your Machine

Your machine has several external controls and components to get familiar with.

Front




Back



Getting Inside

If you need to access the interior components (for accessing settings or troubleshooting), there are 2 ways of getting access:

Front Access Door



Front Access Door

Use the access keys to open the front access door (highlighted). Opening the front access door gives easy access to:

- The Settings switch
- Credits Switch


Rear Access Panel



Use the access keys to open the rear access panel (highlighted).
Opening the rear access panel gives access to:

- Main Board
- Electrical Connections

Wheels and Feet




Your ArcadeMAX system is on castor wheels that allow for easy moving of the machine and 4 retractable feet that can keep the machine in place.

The retractable feet are on screw threads that can be turned either by hand or with a 22mm spanner. Use the spanner to turn the feet to the desired position.

Powering Up and Powering Down

The machine requires a single wall power socket to operate.



Plug the power cable into the wall power socket, then into the power plug on the rear of the machine.

Switch On



Enable power to the machine by flipping both Master Power Switches to on. One switch is next to the power plug. The second is on the top of the machine. **Both switches should glow when switched on.**

Turning On the Internal PC




Power the internal PC up by pressing the PC Power Button on the front of the machine.

Power the internal PC down by pressing the Power Button once you have finished using the machine.

WARNING - The internal PC MUST be powered down before flipping either master power switch. Failure to do so could result in corrupted system settings.

Controlling the Lights:

Lighting Switch



This ArcadeMAX machine includes lighting on the underside of the cabinet that can be turned on or off depending on your preference. Flip the lighting switch on the back of the machine to switch the lighting either on or off.

The lighting can be switched and left on regardless of whether the machine's internal PC is switched on or not allowing for games room ambience when the machine is not in use.

Volume Control




Your machine's sound amplifier controls are accessible on the front of the machine. The sound can be switched on or off with the button on the left. The main volume dial will be illuminated when switched on.


You have 3 dials to adjust the bass, treble and overall volume.

SSD Card Reader

Your machine also comes with a small reader for SSD cards. Whilst this is not used in typical operation of your machine, it should be retained for troubleshooting purposes when in contact with technical support.

Gameplay Controls






Player 2
Start



Pause




Trackball



Trackball

The machine has a trackball in the centre of the main control panel for certain games that use trackball control.

Light Guns




The system includes 2 light guns that can be used to play light gun games.



When not in use, these can be holstered in the holders on each side of the machine.

Force-Feedback Recoil



**Force-Feedback
Recoil Switches**

Each light gun is also equipped with force-feedback for immersive gun recoil effects. This can be switched on or off at the machine with the switches on the front of the cabinet (one for each light gun).

Note – The force-feedback functionality can cause the light guns to overheat if used for prolonged periods. It is best to limit use of this feature for 30 minutes at a time. Allow time for the gun to cool down again before resuming use.

This page is intentionally left blank.



Initial Set Up

Your system will load the main ArcadeMAX games menu once it is fully booted up.


You will need to set up the machine's internet connection and wireless keyboard before being able to proceed further.

Connecting the Included Keyboard



Whilst not necessary for most games, your ArcadeMAX machine includes a wireless keyboard with built-in trackpad. This is needed in order to access certain machine settings.

The keyboard is easy to set up, requiring one AA battery (not included) and the included Keyboard dongle.



Battery
Compartment

Wireless
Dongle

1. To set up, Remove the battery cover on the back of the keyboard and insert 1 AA battery. The Keyboard Dongle can be found within the battery compartment and can be stored here when not in use.
- 2.

Front USB
Port



3. Plug the keyboard dongle into the front of the machine using the front USB port and switch on the keyboard using the on/off switch. It will automatically connect to the machine. You can verify a connection

has been made by using the trackpad to move a mouse cursor around the screen.

4. The bottom of the touch pad features buttons that allow you to click on or otherwise interact with the system.
5. You can switch the keyboard off when not in use to preserve battery life.

Connecting to the Internet

To use the machine and download games to play, you must connect your machine to the internet. Your ArcadeMAX machine can get online in one of two ways:

- Wired ethernet connection (More stable and reliable)
- Over Wi-Fi (More convenient)

Connecting via Ethernet Cable



Network Connector
Port

To connect the machine to the internet via a wired connection, plug a network-connected ethernet cable into the back of the machine into the Network Connector Port until it clicks. You'll be online and ready to start downloading games.

CAUTION

Be aware of moving the machine when connected using a wired internet connection so as not to strain the cable. Tugging at the cable can damage the cable, the plug or the machine's network connector.

Connecting Via Wi-Fi

To connect the machine to a Wi-Fi network, you will need to use the machine's included wireless keyboard (see above for details on use and how to connect)

Access the machine's Wi-Fi settings by hitting **ESC** on the keyboard to leave the main games menu and then click the Wi-Fi settings icon in the bottom right of the screen. Look for the following icon:



You can use this to find your own home Wi-Fi network and input any required credentials.

Return to the games menu by double clicking the **WPlayer.exe icon** on the desktop.

Once complete, your machine will be online and ready to start downloading games.

You can check your internet connectivity strength by referring to the Wi-Fi indicator in the top right of the machine's main games menu.


Light Gun Calibration

Each light gun will have had basic calibration from the time of manufacture. However, to ensure the best play experience, it is strongly recommended to do your own calibration once the machine is set up before playing.


Calibration Tips:

- Darken the room as much as possible for the best possible results
 - UV light (such as from an open window) can interfere with the light gun sensors.
- Ensure the front light gun sensor is not blocked
- Stand 5ft - 6ft from the screen when calibrating
- Ensure your shooting position is below the sensor
- Keep the light gun upright throughout the calibration process
 - Tilting the light gun during this process can lead to erratic results.
- Throughout calibration, hold the light gun in the way you intend to use it.
 - le – If your preferred playing position is aiming through the gun's sights, then use the gun in this way whilst calibrating.
 - If you decide to change the way you hold the light gun, it is advised to recalibrate the light gun to account for the new position.


The Calibration Process




On the system's main menu screen, hold the "Up" directional button on the side of the light gun for approximately 10 seconds to initiate calibration mode. You will know it has begun when the on-screen crosshair moves to the upper-left portion of the screen and begins to flash.



Aim the light gun at the crosshair using your preferred playing position, then pull the trigger.



Once confirmed, the on-screen crosshair will move to the top-right section of the screen and begin to flash. Aim the light gun at the new crosshair using your preferred playing position, then pull the trigger.



Once confirmed, the on-screen crosshair will move the bottom-middle section of the screen and begin to flash. Aim the light gun at the new crosshair using your preferred playing position, then pull the trigger.

The on-screen crosshair will flash in the same position one more time. Aim the light gun at the new crosshair using your preferred playing position, then pull the trigger to finish the calibration process.



Following this, the calibration process is complete, and you should be able to see the aim of the light gun with the on-screen crosshair.

This calibration process will need to be repeated for the other light gun.

Note: If you hit a stage of the calibration process that you're unable to progress beyond, something about your shooting position/style may not be suitable for play.

Adjust the gun height, position (or some other factor) to complete the process, then repeat the calibration process again in the new position.

Using The Main Menu



When switched on, your machine will automatically load the main games menu.

The main menu on the ArcadeMAX system is your home base for playing games on your system. Use it to look through the games list, search for games or even assign favourites.

Basic Menu Controls (Main Panel)



Joystick

Up: Move up 1 selection

Down: Move down 1 selection

Left: Move back one page

Right: Move forward one page



Player 1 A Button

Play current selection



Player 1 C Button

Add current selection to favourites



Player 1 Start Button

Search Tab (Shortcut)

Basic Menu Controls (Light Gun)



D Pad

Up: Move up 1 selection

Down: Move down 1 selection

Left: Move back one page

Right: Move forward one page



“Grenade” Button (Left side)

Play current selection



“Grenade” Button (Right side)

Search Function



Trigger

Not Used


Selecting A Game To Play

Games can be selected either with the controls on the main control panel or from the light guns.

For the sake of brevity, this manual will refer primarily to the main panel controls. Please refer to the table of light gun controls for light gun-specific menu operation.

Use the Player 1 joystick to navigate through the lists, then select your game with the **Player 1 A button**. The game will download to your system and then launch.

The Main Games Menu is also split into different tabs for ease of navigation.



Highlight a tab with the **Player 1 Joystick**, then move left or right to scroll through the tabs.

Adding A Favourite

Any game in the games list can be added to your own favourites list. Press the [Player 1 C Button](#) on any highlighted game to add it to your favourites list.

Favourited games will display a star next to their name.

You can view a collection of all games you have added to your favourites in the “Favourites” tab in the main menu.

Search Functionality



The system includes a very useful search function that can help you find or narrow down your selection in seconds, without having to scroll through the entire games list. You can shortcut to this menu by pressing the [Player 1 Start Button](#) Or by navigating to the search tab (on the far right) at the top of the games list.

Using the Search Functionality



In this menu, you can use the [Player 1 Joystick](#) and [Player 1 A Button](#) to type what you want to search for with the on-screen keyboard. There is no need to input spaces. You can delete letters using the backspace key on the on-screen keyboard.


You also have the option of toggling the genre using the genre toggles (press the [Player 1 A Button](#) whilst on a highlighted option to toggle it on or off)

As you enter in letters, the list on the left will begin to fill with games that match your search term. Jump to the search results with the [Player 1 Start Button](#), then use the [Player 1 Joystick](#) and [Player 1 A Button](#) to select and play any of the search results.

You can add a highlighted game to your favourites by pressing the [Player 1 C Button](#).

When you exit the game, you will return to your original search results, where you can play another result, search for another game or navigate back to the main games lists.

Background Download Mode



This setting must be enabled in settings before it is available. Please refer to page 56 for details.

Under default settings, the machine will load and delete each game individually.

With the Background Download setting enabled, you have the option of downloading up to 5 games in the background whilst playing other games, which can then be started immediately once your current game has finished.

Background Download Mode Controls



Coin Button (In Main Menu)

**Open
Downloads
List**



Joystick

Move



Player 1 A Button (In Downloads List)




**Confirm
Current
Selection**



Player 1 Start Button (In Downloads List)

**Go Back /
Exit**

Menu Buttons

 A dark grey button with rounded corners and a slight gradient, containing the word "Pause" in white text.	Pause the currently selected download.
 A dark grey button with rounded corners and a slight gradient, containing the word "Cancel" in white text.	Cancel/Abort the currently selected download
 A dark grey button with rounded corners and a slight gradient, containing the word "Open" in white text.	Play the currently selected download

How To Use

Select a game from the main menu or your search results as normal and it will be added to your active download list.

From here, you can check the progress of your download, pause the download or cancel the download.

You can download up to 5 games at any one time.

When the game is downloaded and ready to play, navigate to the game's "open" option, and press the [Player 1 A Button](#) to start the game.

You also have the option of returning to the main menu to select another game to download (by pressing the [Player 1 Start Button](#)).

You can check the status of games you have begun downloading at any point from the main menu by pressing the [Coin Button](#).

Note - Like in the default mode, games will automatically be deleted from the machine once they are closed.

In-Game Controls (Main Panel)



Player 1 Start Button

Insert virtual coin and start a 1-player game



Player 2 Start Button

Insert virtual coin and start a 2-player game



Coin Button

Insert additional virtual coins



Pause Button

Bring up Pause Menu

Up: Move up selection



Joystick
(In Pause Menu)

Down: Move down selection



Player 1 A Button

Confirm selection (In Pause Menu)

When a game is loaded, a 1 player game can be started with the **Player 1 Start Button**. A 2-player game can be started with the **Player 2 Start Button**. Pressing either of these buttons also acts as inserting a virtual coin, should the game you're playing require them.

You can add additional virtual coins by pressing the **Coin Button**.

In-Game Controls (Light Gun)



D Pad

Up: Start Button

Down: Insert Coin

Left: Left Pedal/Up

Right: Right Pedal/Down



“Grenade” Button (Left side)

Grenade/Pedal/Reload
(Game Dependent)



“Grenade” Button (Right side)

Reload (Game Dependent)



Trigger

Fire

Note: The exact controls for light gun games may vary slightly from the controls listed depending on the game you're playing.

Listed are some common methods of reloading to try during games:

- Pressing the left or right "Grenade" button
- Aiming and shooting off-screen
- Aiming off-screen

Pause Menu



A game can be paused or quit at any time by pressing the **Pause Button**, where you will be given the option to resume your current game, exit back to the main menu or save or load a game.

Note: It is important to note that any game file downloaded to the system for play is not permanently saved to the system's internal storage. All games by default are deleted immediately upon exiting and will need to be downloaded again.

Please refer to the Game Delete option instructions in the system settings section of this manual (see page 60) if you wish to save and store games indefinitely to the system's internal storage.

Saving and Loading a Game

Note: Only certain games will keep track of high scores. In most cases, every time a game is loaded, it is loaded 'from fresh' meaning that high scores are not saved between games unless saved manually by the player using the saving and loading system.

The saving and loading system may not be supported by every game.

The saving and loading system allow you to save your progress at any point on certain games, and then return to that point at a later time. This is achieved by saving a "State".

About "States"

On this ArcadeMAX system, a "State" can be described as a specific point or moment when in the game. When you load a state, you will return in the game to the exact moment where you saved it.

States can be saved or loaded at any point of the game.

On this system, there can only be one state per game. Each new state you save will overwrite the last.

Save states are unaffected by games being deleted from the system and will be maintained if the game is downloaded again.


How to use

To access the save and load system, pause the game you're currently playing using the **Pause button**, then save the state by scrolling to the "Save State" option and pressing the **Player 1 A Button**.

To load the last state you saved, pause the game using the **Pause button**, then select the "Load State" option from the menu using the **Player 1 A Button**.

This page is intentionally left blank.


System Settings




System settings are changed at a user's own risk. It is recommended to perform the **"Restore Factory Settings"** function (see page 55) on the machine if performance becomes erratic.

This machine has a range of different options that can be changed or modified to change the machine's function to the user's preference.

To access the machine's settings, you must press the machine's settings switch.



On the ArcadeMAX Cosmos, the settings switch can be found inside the front access door.



Press the settings button once to access the settings menu.

Basic Menu Controls



Joystick

Move



Player 1 A Button

**Confirm
Selection/Toggle**



Player 1 Start Button

Go Back / Exit

Outline of Settings Menu Options

Key Setting

- **Keys Testing**

Use this mode to have a visual representation of how the machine responds to inputs. The relevant button will light up on the screen when it is pressed.

- **Key Definition**

Use this mode to remap any of the player buttons to different inputs. You can switch between the machine's default button mapping or your own mapping choices.

Coin Setting

- This setting should always be set to Free Play

Exit Mode

These options allow you to specify a shortcut to quitting the games without having to use the pause menu.

- Start + Coin
 - Press the Player 1 Start Button and the Coin button simultaneously to quit the game.
- Long Press Menu
 - Press and hold the Player 1 Start Button to quit the game.

Auto Exit

Use these options to specify shortcuts or a timeout to exit a game.

- **3 Minutes Exit**
 - Will exit the game automatically after 3 minutes of inactivity.
- **Closed**
 - No shortcuts or automatic timeout will be implemented.

Select Mode

- This setting should always be set to **“Always Allowed”**

Graphic Mode

Use this mode to change the graphics fidelity of certain games.

- **Open**
 - Improved graphics performance.
 - May impact the overall performance of more technically intensive games
- **Closed**
 - Basic graphics performance
 - Most stable mode for running games.

Language

Toggle through the machine’s language settings

Game Setting

Multiple options for changing numerous menu and game settings (see page 57 for more details)

Account Management

Change settings pertaining to various admin-related options and metrics.

- **Clear Coins**
 - Cancel out any virtual coins that have been applied to the system
- **Change Password**
 - Change the system's default Admin password.
 - The default admin password for the machine is 11111111
- **Reset Password**
 - Input the current password to reset the machine's password to the default: 11111111

Restore Factory Settings

If you want to return every system setting to its default, select this option, then confirm your decision in the popup that appears.

Please note that any account management settings (such as passwords) will not be affected by this reset.


Background Download

Use this option to enable background downloading of games (refer to page 38 for details)

- **Closed**
 - Each game is loaded and deleted on an individual basis

- **Open**
 - Up to 5 games can be downloaded in the background.

Game Setting Options



The Game Setting option in the settings menu can be used to modify a wide range of settings, as listed below. You can return to the main settings list at any time using the Player 1 Start button.

Game Difficulty Setting

Use this setting to modify the difficulty of supported games in the games list.

- Navigate the list using the Player 1 Joystick to highlight the game you want to modify.
- Press the **Player 1 A Button** to increase the difficulty. (will reset to 0 beyond the maximum possible number)

- Press the **Player 1 B Button** to increase the number of lives (will reset to 0 beyond the maximum possible number)
- Press the **Player 1 C Button** to apply the current settings to all games in the games list.
- Press the **Player 1 Start Button** to exit and save these settings.

Edit Game List

Use these settings to hide certain games from the main games list from view.

- Navigate the list using the **Player 1 Joystick** to highlight the game you want to modify.
- Press the **Player 1 A button** to hide the currently highlighted game.
- Press the **Player 1 B button** to hide every game in the list.
- Press the **Player 1 C button** to show every game in the list.
- Press the **Player 1 Start Button** to exit and save these settings.

Game Time

This setting is only used with specific coin settings. Please ignore this option.

Force Timing All Games

This option will force all games to operate on a timer, closing them once time is elapsed. For Free-Play purposes, ensure the “Closed” option is selected.

Time Notification Strategy

This option pertains to the Force Timing option above.

- **Always**
 - The remaining time is always displayed on-screen
- **Default**
 - The remaining time is only shown when either Start Button is pressed.

Cursor

This option will either hide or display a cursor on screen.

- **Show:** Cursor will be displayed.
- **Hide:** Cursor will be hidden.

Delete Games

This option will control how the system deals with downloaded games once they are closed.

- **Open**
 - Games will be deleted immediately upon closing.
- **Closed**
 - Games will be saved indefinitely to the machine's internal storage. You must accept the conditions of the popup before this feature can be enabled.

WARNING - Disabling the machine's game deletion functionality can cause legal issues pertaining to copyright. Users choosing to utilise this functionality are accepting full legal responsibility for doing so.

Machine Specifications

CPU	Intel Celeron N5095
RAM	4GB DDR4
Installed SD Card	240GB
System Base	Pandora
Video	HDMI (1280 x 720 - 720P)
Connectivity	<ul style="list-style-type: none"> ● Wireless Keyboard ● Spare USB for Dongle ● Wireless Internet ● Wired Ethernet
Control Peripherals	<ul style="list-style-type: none"> ● Player 1 Control Buttons (x9 (inc start button)) ● Player 2 Control Buttons (x9 (inc Start Button))
Installed Languages	<ul style="list-style-type: none"> ● English ● Korean ● Spanish ● Chinese
Custom Button Mapping	YES
Changeable Game Settings	<ul style="list-style-type: none"> ● Game Difficulty ● Number of Lives
Emulator Search Parameters	<ul style="list-style-type: none"> ● Dreamcast ● Nintendo 64 ● MAME ● Playstation Portable ● Playstation ● Famicom ● Super Famicom

	<ul style="list-style-type: none"> ● Gameboy Advance ● Megadrive ● Final Burn Alpha ● PC Engine ● SEGA NAOMI ● Atomiswave ● SEGA Saturn ● Model 2
Game Category Search Parameters	<ul style="list-style-type: none"> ● Fighting ● Shooting ● Puzzle ● Action ● Sport ● Racing ● 4 Player ● Lightgun ● Trackball
Coin Function	Free Play
Working Environment	5°C - 45°C/ Humidity 30% - 90%

Troubleshooting

Issue	Possible Cause/Solution
No Sound	Check the machine's amplifier is turned on and is turned up.
No Image Signal	<p>The cable connecting the main board to the monitor may have become disconnected or faulty.</p> <p>Verify the main board and the monitor are connected and if so, replace the HDMI cable running from the main board to the monitor.</p>
Unable to download games	<p>The games cloud may temporarily be down, or the machine may be having internet connectivity issues.</p> <p>Check the machine's internet connectivity (with the Network indicator on the main menu) and update Wi-Fi settings if necessary.</p>
Buttons not working	First, verify if a button is working or not in the game's settings via the Keys Test (see page 53). Contact our team and we can help you further.

<p>Light gun issues</p>	<p>Light guns can be quite sensitive to the surrounding environment and the way in which they are used. Make suitable adjustments to your play style or environment and try recalibrating (see page 27)</p>
<p>Light Gun force-feedback weakens over time</p>	<p>After prolonged play, the force-feedback mechanism may appear to lose power. This is due to overheating. Switch off the force-feedback at the buttons on the cabinet and allow the guns to cool down again.</p>

If you have any other issues, or any of the above does not solve your issue, contact us (Contact details on the back of this booklet)



Any other questions?
Tel - 0800 622 6464
sales@homeleisuredirect.com

ARCADE **MAX**